



Heavy duty enclosure

# RBH ENCL2/ENCL2-PS

Robust enclosure with great features  
with ample space for different devices and great ease of installation

[www.rbh-access.com](http://www.rbh-access.com)

# RBH ENCL2 / ENCL2-PS

is a robust enclosure designed to house up to two UNC100 / UNC-500 / RC2M / IOC16M panels or up to six NURC-2002-B\*\* panels

It features a convenient removable cover mounted on heavy duty hinges and allowing 180° swing, lock and a tamper switch.

Installation is made convenient by a number of conduit access points on all sides of the enclosure.



## Features:

- Removable Door
- Lock With 2 Keys
- Tamper Switch
- 2-Stage Knock Outs
- PS-1224 Mount
- Ventilation Slats
- Optional Adapter Plate

## Works With:

### Reader Controllers

- RC2M / NURC-2002-B\*\* / NIRC-2000-B\*\*

### Input/Output Controller

- IOC16M

### Universal Controllers

- UNC100-xxx-M / UNC500-xxx-M

### Axiom Adapter Plate

- AX-MNT-PLT

\*\* Requires AX-MNT-PLT Optional Adapter Plate

## RBH-ENCL2

### Includes:

- Lock with 2 Keys
- Tamper Switch

## RBH-ENCL2-PS

### Includes:

- Lock with 2 Keys
- Tamper Switch
- PS-1224 Power Supply
  - In: 16.5 VAC 40 VA
  - Out: 12 VDC @ 2.5A

## Specifications

Housing	Metal housing with 4 mounting holes
---------	-------------------------------------

### Dimensions:

Width	21" (53 cm)
-------	-------------

Height	17" (43 cm)
--------	-------------

Depth	4 1/2" (11.5 cm)
-------	------------------

Conduit Access:	14
-----------------	----

Top	3 of 22 stage: 3/4" and 1" knockouts
-----	--------------------------------------

Bottom	3 of 22 stage: 3/4" and 1" knockouts
--------	--------------------------------------

Left	3 of 22 stage: 3/4" and 1" knockouts
------	--------------------------------------

Right	3 of 22 stage: 3/4" and 1" knockouts
-------	--------------------------------------

Back	2 of 2" knockouts
------	-------------------


Tamper Switch	N.O. 2A max
---------------	-------------

Weight	19 lbs (8.6 Kg)
--------	-----------------



## ENCL2-PS shown with door off

1 x UNC-500-432M, 3 x NURC-2002-B & 1 x AX-MNT-PL



## AX-MNT-PLT Optional Adapter Plate

Accommodates up to three NURC-2002-B or one NIRC-2000-B

## How to order:

RBH-ENCL2: (Enclosure only)


RBH-ENCL2-PS: (Enclosure with power supply)



RBH Access Technologies, Inc.  
2 Automatic Road, Suite 108  
Brampton ON L6S 6K8, Canada

1-905-790-1515  
1-905-790-3680

[info@rbh-access.com](mailto:info@rbh-access.com)



[www.rbh-access.com](http://www.rbh-access.com)